

# Voicemail Quick Start Card

#### **Main Menu Options**

- 1-New Messages
- 2-Change Folders
- 3-Advanced Options (not Available)
- 0-Voice Mailbox Options
- \*-Repeat the Menu Options
- #-Exit from the Voice Mail System

### **Change Folder Options**

- 0-New Messages
- 1-Old Messages
- 2-Work
- 3-Family
- 4-Friends
- #-Return to Main Menu

#### **Voice Mailbox Options**

- 1-Record your unavailable message
- 2-Record your busy message
- 3-Record your name
- 4-Record your temporary Greeting
- 5-Change your password

### **Create a Voice Message Options**

MTE mail asks you to record the message after the tone.

When you are finished, dial # or hang up.

Either action disconnects your all and stores the message in the "New" messages folder.

## Record a Message/Greeting

MTE mail asks you to record the message after the tone.

After the tone say your message, and then press# key.

MTE mail gives you these options:

- 1-Accept this recording
- 2-Listen to recording
- 3-To re-record your message

### **Change Your Password**

MTE mail asks you to enter your new password followed by #.

Enter your new password, and #.

MTE mail asks you to re-enter your new password followed by #.

MTE mail confirms that your password has been changed, and returns you to the Voice Mailbox options.

#### **Voicemail Retrieval**

\*From your Subscribed phone Pick up the handset.

Dial \*83

\*From any other location Pick up the handset.

Dial your phone number.

Press \*

Enter your 10-digit phone number.

Listen for the prompt for your password.

#### Voicemail Message Controls

1-Interrupt message introduction

\*-Rewind the message by 3 seconds

#-forward the message by 3 seconds

After the message has played:

- 5-Repeat current message
- 6-Play the next message
- 7-Delete this message
- 8-forward this message 9-Save this message